



Approximate Fuel Consumption Chart

Please Note: The below table is intended to be used as an estimate of how much fuel a generator consumes during operation. Actual fuel consumption may vary by make and model of engine. Please consult the manufacturer's specification sheet for exact fuel consumption details.

Generator Size (kW)	1/4 Load (gal/hr)	1/2 Load (gal/hr)	3/4 Load (gal/hr)	Full Load (gal/hr)
20	0.6	0.9	1.3	1.6
30	1.3	1.8	2.4	2.9
40	1.6	2.3	3.2	4
60	1.8	2.9	3.8	4.8
75	2.4	3.4	4.6	6.1
100	2.6	4.1	5.8	7.4
125	3.1	5	7.1	9.1
135	3.3	5.4	7.6	9.8
150	3.6	5.9	8.4	10.9
175	4.1	6.8	9.7	12.7
200	4.7	7.7	11	14.4
230	5.3	8.8	12.5	16.6
250	5.7	9.5	13.6	18
300	6.8	11.3	16.1	21.5
350	7.9	13.1	18.7	25.1
400	8.9	14.9	21.3	28.6
500	11	18.5	26.4	35.7
600	13.2	22	31.5	42.8
750	16.3	27.4	39.3	53.4
1000	21.6	36.4	52.1	71.1
1250	26.9	45.3	65	88.8
1500	32.2	54.3	77.8	106.5
1750	37.5	63.2	90.7	124.2
2000	42.8	72.2	103.5	141.9
2250	48.1	81.1	116.4	159.6
2500	59.5	95.7	132.0	168
2750	63.3	103.4	143.4	183.4
3000	67.0	113.0	158.0	203
3250	73.0	122.0	171.0	221
3500	77.0	130.0	183.0	236